



3C-WDM-1000-35-60(Type A)

3C-WDM-1000-53-60(Type B)

10/100/1000M SINGLE FIBER MEDIA CONVERTER, 60KM

20100425-1188

10/100/1000Base-T to 1000Base-SX/LX Gigabit Media Converter

For the flexibility with all kind 10/100/1000Mbps Ethernet Media on RJ-45 port and high stable Gigabit fiber performance. 3c-Link release the 3C-WDM-1000 of Media Converters supports conversion between 10/100/1000Base-T and 1000Base-LX/SX network, there are SC connectors with Single-mode media as required. The Ethernet signal allows three types of segments to connect easily, efficiently.

To centralize the fiber-optic network installation, the 10/100/1000M Media converter with compact design can be used as standalone unit as well as being installed to the media chassis such as the 3C-LINK 3C-MC-R14, 14-slot Media Converter Chassis. These media chassis can assist in producing the power for 3C-Link 10/100/1000 Media Converter to maintain the fiber-optic network at one location

As the Gigabit Media Converter fully complies with IEEE 802.3 10Base-T, IEEE 802.3u 100Base-TX, IEEE 802.3ab 1000Base-T and IEEE 802.3z 1000Base-ZX, the Gigabit media conversion installation is quite quick

and easy by simple plugging and playing feature. also supports flow control and back pressure in half-duplex to eliminate packets loss

Key Feature

- Complies with IEEE 802.3 10Base-T, IEEE 802.3u 100Base-TX, IEEE802.3ab 1000Base-T, IEEE 802.3z 1000Base-SX/LX/ZX
- TP port supports 10/100/1000Base-T auto-negotiation and auto-MDI/MDI-X
- 1000Base-ZX: 9/125μm multi-mode fiber cable, up to 60 Km (3C-WDM-1000-35/53-60)
- Layer 2 key Feature:
 - IEEE 802.3x Full-Duplex Flow-Control and Back-Pressure in Half-Duplex eliminate the loss of packets
 - Support auto MDI/MDI-X function
 - Store-and-Forward mechanism
 - Non-blocking full wire-speed forwarding rate
- Media conversion between 10/100/1000Base-T and 1000Base-SX/LX/ZX
- Fiber media allows:
 - Multi-mode fiber using SC/LC/WDM connector
 - Single-mode fiber using SC/LC/WDM connector
- Compacts size for working with 3C-LINK Media Chassis(3C-MC-R14)
- LED indicators for easy network diagnose
- Compact in size, easy installation
- Choice of fiber-connector from SC, LC and WDM multi-mode /single-mode fiber for 1000Base SFP interface

Specification

Products	Gigabit Ethernet Media Converter
Model	3C-WDM-1000-35/53-60
Standards	IEEE 802.3, 10Base-T IEEE 802.3u, 100Base-TX IEEE 802.3ab, 1000Base-T IEEE 802.3z, 1000Base-SX/LX
Ports	1 x 10/100/1000Base-T port, 1 x 1000Base-ZX port
Copper Interface	RJ-45 port (Auto-MDI/MDI-X) Twisted Pair
Optic Interface	SC/ST
Optic Wavelength	1310/1550nm
Speed	10/20Mbps for Half/Full Duplex 100/200Mbps for Half/Full Duplex 1000/2000Mbps for Half/Full Duplex
UTP Cable	10Base-T: 2-pair UTP Cat. 3,4,5, up to 100 m 100Base-TX: 2-pair UTP Cat. 5, up to 100 m 1000Base-T: 4-pair STP Cat 5 up to 100m
Fiber Cable	9/125 μ m single-mode fiber cable, up to 60km
LED Indicator	PWR TP LINK/ACT, 1000 Fiber LINK/ACT
Power Consumption	4.0 Watts(Max)
Power Input	DC 5V/1.5A
Dimensions (W x D xH)	26 x 70 x 97 mm
Operator Environment	Operating temperature: 0 to 50 degree C; Humidity: 5~90% non-condensing
Storage Environment	storage temperature: -40 to 70 degree C; Humidity: 5~90% non-condensing

Application



Order Information

3C	-	X		X	-	X	-	X	-	X
		Type	-	Data rate		Wave Length		Distance		Support Chassis
		WDM		100=10/100M		85=850nm		20=20Km		R14
		DU		1000=10/100/1000		13=1310nm		40=40Km		R16
						15=1550nm				R16M
						35=1310T/1550R				R16SM
						53=1550T/1310R				
						45=1490T/1550R				
						54=1550T/1490R				

For Example:

3C-WDM-1000-35-60: 10/100/1000M media converter, 1310T/1550R, 60KM, SC

3C-WDM-1000-53-60: 10/100/1000M media converter, 1550T/1310R, 60KM, SC



Specifications are subject to change without notice. It is a registered trademark of 3C-LINK Technology Co., Ltd. Other brands and product names are trademarks or registered trademarks of their respective holders. No part of the specifications can be reproduced in any form or by any means or used to make any derivative such as translation, transformation, or adaptation without permission from 3C-LINK Technology Co., Ltd.